

# 6500W DUAL FUEL INVERTER GENERATOR



Image for illustration purpose only

**Starting Power** 6500 / 6000W (Gasoline/LPG)

**Rated Power** 5500 / 5000W (Gasoline/LPG)

**Noise Level** 60dB

**Frequency** 50 Hz/60 Hz







## FEATURES

- Ultra Quiet: 60 dBA
- Dual Fuel: Powered by Either Gasoline or LPG
- Compact: 638×499×543mm
- Long Run Time @50 %Load: 9.5 Hours
- Eco Throttle: More Efficient
- Starting Method: Push Button or Remote Start
- Safe Clean Power: Power Sensitive Electronics
- Stronger Together: Parallel for Double Power
- Built-in Mobility Kit with Telescopic Handle

## SPECIFICATION



MODEL	A6500DFi
Max Starting Power	6500W Gas / 6000W LPG
Running Power	5500W Gas / 5000W LPG
AC Load (Volts)	240
Phase, Frequency	Single, 50Hz/60Hz
Rated Amperage	23.9(Gasoline) , 21.7(LPG)
Starting Method	Manual/E-Start/Remote
Engine Type	Gasoline
Engine Model/CC/Hp	SV320B/322cc/9.5Hp
Noise Level	60dB
Fuel Tank Capacity	13.5L
Run Time-50 %Load	9.5Hrs
Run Time-100 %Load	5.5Hrs
Fuel Consumption(Gasoline)	2.4L/Hr (100 %Load)
Fuel Consumption (LPG)	1.46Kg/Hr (100 %Load)
Engine Oil Capacity	0.7L
Digital Display	9-in-1 Meter
Circuit Breaker	1x20A, 1x30A, 1x50A
Eco-Throttle	√
Parallel Port	√
Socket	1x20A, 1x30A, 1x50A
DC Port	√
THD	<%3
Battery	5AH
Wheel	7in
Plug	1x20A, 1x30A, 1x50A
Net / Gross Weight	58 / 65Kg
Prodcut Dimension(LxWxH)	638x499x543mm



## GREAT CHOICE FOR:

