

	MODEL	A12000CE
	Max Starting Power	8000W
	Running Power	7000W
	AVR	$\sqrt{}$
ı	AC Load (Volts)	230
	Phase, Frequency	Single, 50Hz
	Rated Amperage	30.4A
	Starting Method	Manual/E-start
ı	Engine Type	OHV, Air-Cooled, Gasoline
	Engine Model/CC/Hp	190FD/420cc/14Hp
	Low Oll Shut Down	$\checkmark$
	Fuel Tank Capacity	40L
	Run Time-50 %Load	15.0Hrs
	Run Time-100 %Load	12.0Hrs
	Fuel Consumption (50 %Load)	2.6L/Hr
	Engine Oil Capacity	1.1L
	Display	3-in-1 Meter
	Low Oil Alert Lamp	$\sqrt{}$
	Circuit Breaker	1x16A, 1x29A
	Socket	1x16A, 1x32A
	Steel Frame	Ф28
	Fold Down Handle	$\sqrt{}$
	Battery	14AH
	Spark Plug Socket	$\sqrt{}$
	Plug	1x32A
	Wheel Kits	$\sqrt{}$
	Net Weight	90Kg
	Gross Weight	94.5Kg
	Packing Dimension(LxWxH)	730x555x630mm

110/256

Q'ty (20GP/40HQ)

## A12000CE GASOLINE GENERATOR

## **FEATURES**

- Volt-Reduce Start Technology
- ◆ Easy Recoil and Key Start
- ◆ 420cc/14hp Powerful Gasoline Engine
- ◆ High Performance Surge Alternator
- ◆ 40L Heavy Duty Large Fuel Tank
- Long Run Time @50 %Load: 15 Hours
- Intelligent Siliconed AVR
- ◆ Digital 4-in-1 Hour Meter
- ◆ Built-in Fuel Gauge
- ◆ Low Oil Shutdown
- Rigid Low Tone Muffler
- Never-Flat Wheel for Effortless Move



