

## **TECHNICAL DATA**

MODEL	A15000CE
Max Starting Power	9000W / 11.25kVA
Running Power	8000W / 10kVA
AVR	$\checkmark$
AC Load (Volts)	230
Phase, Frequency	Single, 50Hz
Rated Amperage	34.8A
Starting Method	Manual/E-start
Engine Type	OHV, Air-Cooled, Gasoline
Engine Model/CC/Hp	192FBD/459cc/16Hp
Low Oll Shut Down	$\checkmark$
Fuel Tank Capacity	40L
Run Time-50 %Load	15.0Hrs
Run Time-100 %Load	12.0Hrs
Engine Oil Capacity	1.1L
Display	3-in-1 Meter
Low Oil Alert Lamp	$\sqrt{}$
Circuit Breaker	1x16A, 2x32A,1x35A
Socket	1x16A,2x32A,AC Terminal
Steel Frame	Ф28
Fold Down Handle	$\sqrt{}$
Battery	14AH
Spark Plug Socket	$\sqrt{}$
Plug	1x32A
Wheel Kits	$\checkmark$
Net Weight	106Kg
Gross Weight	112Kg
Packing Dimension(LxWxH)	730x555x630mm
Q'ty (20GP/40HQ)	110/256

## A15000CE GASOLINE GENERATOR

## **FEATURES**

- ◆ Volt-Reduce Start Technology
- ◆ Easy Recoil and Key Start
- ◆ 456cc/16hp Powerful Gasoline Engine
- ◆ High Performance Surge Alternator
- ◆ 40L Heavy Duty Large Fuel Tank
- Long Run Time @50 %Load: 15 Hours
- ◆ Intelligent Siliconed AVR
- ◆ Digital 4-in-1 Hour Meter
- ◆ Built-in Fuel Gauge
- Low Oil Shutdown
- Rigid Low Tone Muffler
- Never-Flat Wheel for Effortless Move



