

A3500Di



SILENT INVERTER GENERATOR



FEATURES

- ◆ Quiet: 58 dBA
- ◆ Light: 24 kgs
- ◆ Compact: 500×310×475mm
- ◆ Long Run Time @50 %Load: 6 Hours
- ◆ Eco Throttle: More Efficient
- ◆ Starting Method: Easy Recoil Start
- ◆ Safe Clean Power: Power Sensitive Electronics
- ◆ Stronger Together: Parallel for Double Power
- ◆ 50/60Hz: Versatile for Powering Worldwide Electronics
- ◆ Built-in Mobility Kit with Telescopic Handle



TECHNICAL DATA

MODEL	A3500Di
Max Starting Power	3500W
Running Power	3000W
AC Load (Volts)	230
Phase, Frequency	Single, 50/60Hz
Rated Amperage	13.0A
Starting Method	Manual
Engine Type	Gasoline
Engine Model/CC/Hp	SH150B/149cc/5.5Hp
Noise Level	58dB
Fuel Tank Capacity	6.0L
Run Time-50 %Load	6.0Hrs
Run Time-100 %Load	3.5Hrs
Fuel Consumption (50 %Load)	1.0L/Hr
Engine Oil Capacity	0.48L
Digital Display	9-in-1 LED Meter
Circuit Breaker	9A, 16A
Remote Control	N/A
Eco-Throttle	√
Parallel Port	√
Socket	1x16A, 1x30A
DC Port	√
THD	<%3
Battery	N/A
Wheel	2.7inch
Plug	1x30A, DC Plug
Net Weight	24Kg
Gross Weight	28Kg
Packing Dimension(LxWxH)	560x365x515mm
Prodcut Dimension(LxWxH)	500x310x475mm
Q'ty (20GP/40HQ)	256/640

