

A6500iD50



SILENT INVERTER GENERATOR



FEATURES

- ◆ Quiet - 60 dBA
- ◆ Light - 58 kgs
- ◆ Compact - 638×499×543mm
- ◆ Long Run Time @50 %Load: 9.5 Hours
- ◆ Eco Throttle - More Efficient
- ◆ Starting Method - Push Button or Remote Start
- ◆ Safe Clean Power - Power Sensitive Electronics
- ◆ Stronger Together - Parallel for Double Power
- ◆ Dual Fuel: Powered by Either Gasoline or LPG
- ◆ Built-in Mobility Kit with Telescopic Handle

TECHNICAL DATA

MODEL	A6500iD50
Max Starting Power	6500W Gasoline/6000W LPG
Running Power	5500W Gasoline/5000W LPG
AC Load (Volts)	230
Phase, Frequency	Single, 50Hz
Rated Amperage	23.9 Gasoline / 21.7 LPG
Starting Method	Manual/E-Start/Remote
Engine Type	Gasoline
Engine Model/CC/Hp	SV320B/322cc/9.5Hp
Noise Level	60dB
Fuel Tank Capacity	13.5L
Run Time-50 %Load	9.5Hrs
Run Time-100 %Load	5.5Hrs
Fuel Consumption (50 %Load)	1.4L/Hr
Engine Oil Capacity	0.7L
Digital Display	9-in-1 LED Meter
Circuit Breaker	1x20A, 1x30A, 1x50A
Remote Control	√
Eco-Throttle	√
Parallel Port	√
Socket	1x16A, 1x32A
DC Port	√
THD	<%3
Battery	5AH
Wheel	7 inch
Plug	1x32A
Net Weight	58Kg
Gross Weight	65Kg
Packing Dimension(LxWxH)	715x665x610mm
Prodcut Dimension(LxWxH)	638x499x543mm
Q'ty (20GP/40HQ)	96/264

