



## **TECHNICAL DATA**

MODEL	ADG12000ES-3EP
Max Starting Power	9000W / 11.25kVA
Running Power	8000W / 10.0kVA
High Performance Alternator	
AVR	$\checkmark$
AC Load (Volts)	230/380
Phase, Frequency	Single/Three,50Hz
Rated Amperage	34.8A/12.1
Starting Method	Electric
Engine Type	Diesel
Engine Model/CC/Hp	688F/633cc/13Hp
Low OII Shut Down	$\sqrt{}$
Fuel Tank Capacity	15L
Run Time-50 %Load	10.0Hrs
Run Time-100 %Load	6.0Hrs
Fuel Consumption (50 %Load)	2.3L/Hr
Engine Oil Capacity	1.65L
Noise Level at 7m	70dBA
Display	3-in-1 Meter
Low Oil Alert Lamp	$\sqrt{}$
Circuit Breaker	32A
Socket	2x30A
Steel Frame	Canopy
Built-in Handle	$\sqrt{}$
Battery	28AH
Spark Plug Socket	/
Plug	$\checkmark$
Wheel Kits	4 inch
Net Weight/Gross Weight	185 kg / 195 Kg
Packing Dimension(LxWxH)	1120x630x945 mm

## ADG12000ES-3EP DIESEL GENERATOR

## **FEATURES**

- Quiet: 70dBA
- ◆ Easy Electric Key Start
- ◆ High Performance Alternator
- ◆ 688F/633cc/13hp Powerful Diesel Engine
- ◆ Long Run Time @50 %Load: 8 Hours
- ◆ ATS Port Ready for Non-stop Power Supply
- ◆ Intelligent AVR Delivers Stable Power
- ◆ Digital 3-in-1 Hour Meter
- ◆ Low Oil Shutdown
- ◆ Rigid Canopy for Low Tone Operation
- Never-Flat Wheel for Effortless Move