

# IN8000CE

## GASOLINE GENERATOR



### FEATURES

- ◆ Easy Recoil and Key Start
- ◆ 389cc/13hp Powerful Gasoline Engine
- ◆ High Performance Alternator
- ◆ Long Run Time @50 %Load: 12 Hours
- ◆ Intelligent Siliconed AVR
- ◆ Digital 3-in-1 Hour Meter
- ◆ Built-in Fuel Gauge
- ◆ Low Oil Shutdown
- ◆ Rigid Low Tone Muffler
- ◆ Never-Flat Wheel for Effortless Move

### TECHNICAL DATA

MODEL	IN8000CE
Max Starting Power	6000W
Running Power	5500W
AVR	√
AC Load (Volts)	230
Phase, Frequency	Single, 50Hz
Rated Amperage	23.9A
Starting Method	Manual/E-start
Engine Type	OHV, Air-Cooled, Gasoline
Engine Model/CC/Hp	188FD/389cc/13Hp
Low Oil Shut Down	√
Fuel Tank Capacity	25L
Run Time-50 %Load	12.0Hrs
Run Time-100 %Load	8.0Hrs
Fuel Consumption (50 %Load)	2.1L/Hr
Engine Oil Capacity	1.1L
Display	3-in-1 Meter
Low Oil Alert Lamp	√
Circuit Breaker	√
Socket	1x16A, 1x30A
Steel Frame	Φ28
Fold Down Handle	√
Battery	14AH
Spark Plug Socket	√
Plug	1x30A
Wheel Kits	√
Net Weight	82Kg
Gross Weight	85Kg
Packing Dimension(LxWxH)	720x545x610mm
Q'ty (20GP/40HQ)	96/256

