

# SM6500Di



## SILENT INVERTER GENERATOR



### FEATURES

- ◆ Quiet: 60 dBA
- ◆ Light: 56 kgs
- ◆ Compact: 638×499×543mm
- ◆ Long Run Time @50 %Load: 9.5 Hours
- ◆ Eco Throttle: More Efficient
- ◆ Starting Method: Push Button or Remote Start
- ◆ Safe Clean Power: Power Sensitive Electronics
- ◆ Stronger Together: Parallel for Double Power
- ◆ 50/60Hz: Versatile for Powering Worldwide Electronics
- ◆ Built-in Mobility Kit with Telescopic Handle

### TECHNICAL DATA

MODEL	SM6500Di
Max Starting Power	6500W
Running Power	5500W
AC Load (Volts)	230
Phase, Frequency	Single, 50/60Hz
Rated Amperage	23.9A
Starting Method	Manual/E-Start/Remote
Engine Type	Gasoline
Engine Model/CC/Hp	SV320B/322cc/9.5Hp
Noise Level	60dB
Fuel Tank Capacity	13.5L
Run Time-50 %Load	9.5Hrs
Run Time-100 %Load	5.5Hrs
Fuel Consumption (50 %Load)	1.4L/Hr
Engine Oil Capacity	0.7L
Digital Display	9-in-1 LED Meter
Circuit Breaker	9A, 16A
Remote Control	✓
Eco-Throttle	✓
Parallel Port	✓
Socket	1x32A ,1x16A
DC Port	✓
THD	<%3
Battery	5AH
Wheel	7 inch
Plug	1x32A
Net Weight	56Kg
Gross Weight	63Kg
Packing Dimension(LxWxH)	715x665x610mm
Prodcut Dimension(LxWxH)	638x499x543mm
Q'ty (20GP/40HQ)	96/264

